

Text Comparison

Documents Compared

en_30060904v080002p.pdf

en_30060904v090201p.pdf

Summary

4748 word(s) added

2997 word(s) deleted

2766 word(s) matched

67 block(s) matched

To see where the changes are, please scroll down.

~~ETSI EN 300 609-4 V8.0.2 (2000-10)~~

~~European Standard (Telecommunications series)~~

~~Digital cellular telecommunications system (Phase 2 and Phase 2+);
Base Station System (BSS) equipment specification;
Part 4: Repeaters
(GSM 11.26 version 8.0.2 Release 1999)~~

GSM 
~~GLOBAL SYSTEM FOR
MOBILE COMMUNICATIONS~~

ETSI 

ETSI EN 300 609-4 v9.2.1 (2010-10)

Harmonized European Standard (Telecommunications series)

Global System for Mobile communications (GSM):
Part 4: Harmonized EN for GSM Repeaters
covering the essential requirements
of article 3.2 of the R&TTE Directive



~~Reference~~~~REN/GMO-021126Q8~~~~Keywords~~~~Digital cellular telecommunications system;
Global System for Mobile communications (GSM)~~**ETSI**

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at <http://www.etsi.org/tb/status/>

If you find errors in the present document, send your comment to:

~~editor@etsi.fr~~

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute ~~2000~~.
All rights reserved.

Reference

REN/MSG-00003Keywords

GSM, repeater**ETSI**

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

http://portal.etsi.org/chaicor/ETSI_support.asp

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2010.
All rights reserved.

DECT™, PLUGTESTS™, UMTS™, TIPHON™, the TIPHON logo and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.

3GPP™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

LTE™ is a Trade Mark of ETSI currently being registered for the benefit of its Members and of the 3GPP Organizational Partners.

GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

~~Contents~~

| | |
|---|---------------|
| Intellectual Property Rights | 5 |
| Foreword..... | 5 |
| 1 Scope | 6 |
| 2 References | 6 |
| 3 Definitions and abbreviations..... | 7 |
| 3.1 Definitions | 7 |
| 3.2 Abbreviations | 7 |
| 4 General | 7 |
| 4.1 Radio frequency bands | 7 |
| 4.2 Test environments | 8 |
| 4.2.1 Normal test environment | 8 |
| 4.2.2 Extreme test environment | 8 |
| 4.2.3 Extreme temperature | 8 |
| 4.3 Manufacturers declarations | 9 |
| 4.4 Methods of measurement | 9 |
| 5 Spurious emissions | 9 |
| 5.1 Test purpose | 9 |
| 5.2 Test case | 9 |
| 5.3 Conformance requirement | 10 |
| 5.4 Reference requirement | 11 |
| 6 Intermodulation attenuation | 11 |
| 6.1 Test purpose | 11 |
| 6.2 Test case | 11 |
| 6.3 Conformance requirement | 11 |
| 6.4 Reference requirement | 11 |
| 7 Out of band gain | 12 |
| 7.1 Test purpose | 12 |
| 7.2 Test case | 12 |
| 7.3 Conformance requirement | 12 |
| 7.4 Reference requirement | 12 |
| 8 Frequency error | 12 |
| 8.1 Test purpose | 12 |
| 8.2 Test case | 13 |
| 8.3 Conformance requirement | 13 |
| 8.4 Reference requirement | 13 |
| 9 Modulation accuracy at GMSK modulation..... | 13 |
| 9.1 Test purpose | 13 |
| 9.2 Test case | 13 |
| 9.3 Conformance requirement | 14 |
| 9.4 Reference requirement | 14 |
| 10 Modulation accuracy at 8-PSK modulation | 14 |
| 10.1 Test purpose | 14 |
| 10.2 Test case | 14 |
| 10.3 Conformance requirement | 15 |
| Annex A (informative): Testing of gain for part band repeaters | 16 |
| A.1 Rationale for this test..... | 16 |
| A.2 Gain outside operating band..... | 16 |
| A.2.1 Test purpose | 16 |

Contents

| | |
|---|--------------------|
| Intellectual Property Rights | 5 |
| Foreword | 5 |
| Introduction | 5 |
| 1 Scope | 6 |
| 2 References | 6 |
| 2.1 Normative references | 7 |
| 2.2 Informative references | 7 |
| 3 Definitions and abbreviations | 7 |
| 3.1 Definitions | 7 |
| 3.2 Abbreviations | 8 |
| 4 Technical requirements specifications | 8 |
| 4.1 Environmental profile | 8 |
| 4.2 Conformance requirements | 8 |
| 4.2.1 Conducted spurious emissions | 8 |
| 4.2.1.1 Definition | 8 |
| 4.2.1.2 Limit | 8 |
| 4.2.1.3 Conformance | 9 |
| 4.2.2 Radiated spurious emissions | 9 |
| 4.2.2.1 Definition | 9 |
| 4.2.2.2 Limit | 9 |
| 4.2.2.3 Conformance | 10 |
| 4.2.3 Intermodulation attenuation | 10 |
| 4.2.3.1 Definition | 10 |
| 4.2.3.2 Limit | 10 |
| 4.2.3.3 Conformance | 10 |
| 4.2.4 Out-of-band gain | 10 |
| 4.2.4.1 Definition | 10 |
| 4.2.4.2 Limit | 11 |
| 4.2.4.3 Conformance | 11 |
| 4.2.5 Frequency error | 11 |
| 4.2.5.1 Definition | 11 |
| 4.2.5.2 Limit | 11 |
| 4.2.5.3 Conformance | 11 |
| 4.2.6 Modulation accuracy at GMSK modulation | 11 |
| 4.2.6.1 Definition | 11 |
| 4.2.6.2 Limit | 11 |
| 4.2.6.3 Conformance | 11 |
| 4.2.7 Modulation accuracy at 8-PSK, QPSK, 16-QAM or 32-QAM modulation | 12 |
| 4.2.7.1 Definition | 12 |
| 4.2.7.2 Limit | 12 |
| 4.2.7.3 Conformance | 12 |
| 5 Testing for compliance with technical requirements | 12 |
| 5.1 Environmental conditions for testing | 12 |
| 5.2 Interpretation of the measurement results | 12 |
| 5.3 Essential radio test suites | 13 |
| 5.3.1 Conducted spurious emissions | 13 |
| 5.3.1.1 Initial conditions | 13 |
| 5.3.1.2 Procedures | 13 |
| 5.3.2 Radiated spurious emissions | 14 |
| 5.3.2.1 Initial conditions | 14 |
| 5.3.2.2 Procedures | 14 |
| 5.3.3 Intermodulation attenuation | 14 |
| 5.3.3.1 Initial conditions | 14 |

| | | |
|-----------------------------------|--|---------------|
| A.2.2 | Test case | 16 |
| A.2.3 | Conformance requirement | 16 |
| Annex B (informative): | Change history | 17 |
| History | | 18 |

| | | |
|--------------------------------------|--|------------------|
| <u>5.3.3.2</u> | <u>Procedures</u> | <u>14</u> |
| <u>5.3.4</u> | <u>Out-of-band gain</u> | <u>15</u> |
| <u>5.3.4.1</u> | <u>Initial conditions</u> | <u>15</u> |
| <u>5.3.4.2</u> | <u>Procedures</u> | <u>15</u> |
| <u>5.3.5</u> | <u>Frequency error</u> | <u>16</u> |
| <u>5.3.5.1</u> | <u>Initial conditions</u> | <u>16</u> |
| <u>5.3.5.2</u> | <u>Procedures</u> | <u>16</u> |
| <u>5.3.6</u> | <u>Modulation accuracy at GMSK modulation</u> | <u>16</u> |
| <u>5.3.6.1</u> | <u>Initial conditions</u> | <u>16</u> |
| <u>5.3.6.2</u> | <u>Procedures</u> | <u>16</u> |
| <u>5.3.7</u> | <u>Modulation accuracy at 8-PSK, QPSK, 16-QAM or 32-QAM modulation</u> | <u>17</u> |
| <u>5.3.7.1</u> | <u>Initial conditions</u> | <u>17</u> |
| <u>5.3.7.2</u> | <u>Procedures</u> | <u>17</u> |
| <u>Annex A (normative):</u> | <u>HS Requirements and conformance Test specifications Table (HS-RTT)</u> | <u>18</u> |
| <u>Annex B (informative):</u> | <u>Environmental profile specification</u> | <u>20</u> |
| <u>Annex C (informative):</u> | <u>Testing of gain for part band repeaters</u> | <u>21</u> |
| <u>C.1</u> | <u>Rationale for this test</u> | <u>21</u> |
| <u>C.2</u> | <u>Gain outside pass band</u> | <u>21</u> |
| <u>C.2.1</u> | <u>Test purpose</u> | <u>21</u> |
| <u>C.2.2</u> | <u>Test case</u> | <u>21</u> |
| <u>C.2.3</u> | <u>Conformance requirement</u> | <u>21</u> |
| <u>Annex D (informative):</u> | <u>The EN title in the official languages</u> | <u>22</u> |
| <u>Annex E (informative):</u> | <u>Bibliography</u> | <u>23</u> |
| <u>History</u> | | <u>24</u> |

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://www.etsi.org/ipr>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This European Standard (Telecommunications series) has been produced by ETSI Technical Committee ~~Special~~ Mobile Group (~~SMG~~).

The present document ~~describes the Radio Frequency (RF) tests for GSM 450, GSM 480, GSM 900 and DCS 1800 repeaters within the digital cellular telecommunications system (Phase 2/Phase 2+).~~

~~The contents of the present document may be subject to continuing work within SMG and may change following formal SMG approval. Should SMG modify the contents of the present document it will then be re-submitted for formal approval procedures by ETSI with an identifying change of release date and an increase in version number as follows:~~

~~Version 8.x.y~~

~~where:~~

~~8 - GSM Phase 2+ Release 1999;~~

~~x - the second digit is incremented for changes of substance, i.e. technical enhancements, corrections, updates, etc.;~~

~~y - the third digit is incremented when editorial only changes have been incorporated in the specification.~~

National transposition dates

| | |
|--|------------------------------|
| Date of adoption of this EN: | 22 September 2000 |
| Date of latest announcement of this EN (doa): | 31 December 2000 |
| Date of latest publication of new National Standard or endorsement of this EN (dop/e): | 31 June 2001 |
| Date of withdrawal of any conflicting National Standard (dow): | 31 June 2001 |

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This **Harmonized European Standard** (Telecommunications series) has been produced by ETSI Technical Committee Mobile **Standards** Group (**MSG**).

The present document has been produced by ETSI in response to a mandate from the European Commission issued under Council Directive 98/34/EC [i 1] (as amended) laying down a procedure for the provision of information in the field of technical standards and regulations.

The present document is intended to become a Harmonized Standard, the reference of which will be published in the Official Journal of the European Communities referencing the Directive 1999/5/EC [i 2] of the European Parliament and of the Council of 9 March 1999 on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity ("the R&TTE Directive").

The requirements relevant to Directive 1999/5/EC [i 2] are summarized in annex A.

| National transposition dates | |
|--|-----------------|
| Date of adoption of this EN: | 19 October 2010 |
| Date of latest announcement of this EN (doa): | 31 January 2011 |
| Date of latest publication of new National Standard or endorsement of this EN (dop/e): | 31 July 2011 |
| Date of withdrawal of any conflicting National Standard (dow): | 31 July 2012 |

Introduction

The present document is part of a set of standards developed by ETSI and is designed to fit in a modular structure to cover all radio and telecommunications terminal equipment within the scope of the R&TTE Directive [i 2]. The modular structure is shown in EG 201 399 [i 3].

1 Scope

~~The present document describes the Radio Frequency (RF) tests for GSM 450, GSM 480, GSM 900 and DCS 1800 repeaters which receive, amplify, and retransmit a received Mobile Station (MS) signal in the GSM MS transmit band and simultaneously receive, amplify and retransmit a received Base Transceiver Station (BTS) RF signal in the GSM BTS transmit band.~~

~~The present document is applicable to repeaters meeting the requirements of either GSM Phase 2 or GSM Phase 2+. Unless otherwise stated, all tests are applicable to repeaters meeting Phase 2 and/or Phase 2+ GSM requirements, because the requirements of the Phase 2 and Phase 2+ core GSM specifications which are referenced in the test are consistent. Most differences between Phase 2 and Phase 2+ requirements represent Phase 2+ features which are optional for the BSS to support.~~

2 References

~~The following documents contain provisions which, through reference in this text, constitute provisions of the present document.~~

- ~~References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.~~
- ~~For a specific reference, subsequent revisions do not apply.~~
- ~~For a non-specific reference, the latest version applies.~~
- ~~A non-specific reference to an ETS shall also be taken to refer to later versions published as an EN with the same number.~~
- ~~For this Release 1999 document, references to GSM documents are for Release 1999 versions (version 8.x.y).~~

- [1] ~~ETR 350 (GSM 01.04): "Digital cellular telecommunication system (Phase 2+); Abbreviations and acronyms".~~
- [2] ~~ETS 300 019-1-0: "Equipment Engineering (EE). Environmental conditions and environmental tests for telecommunications equipment Part 1-0, Classification of environmental conditions, Introduction".~~
- [3] ~~ETS 300 019-1-3: "Equipment Engineering (EE). Environmental conditions and environmental tests for telecommunications equipment Part 1-3, Classification of environmental conditions, Stationary use at weather-protected locations".~~
- [4] ~~ETS 300 019-1-4: "Equipment Engineering (EE). Environmental conditions and environmental tests for telecommunications equipment Part 1-4, Classification of environmental conditions, Stationary use at non-weather-protected locations".~~
- [5] ~~ETS 300 113: "Radio Equipment and Systems (RES), Land mobile service, Technical characteristics and test conditions for radio equipment intended for the transmission of data (and speech) and having an antenna connector".~~
- [6] ~~ETS 300 910 (GSM 05.05): "Digital cellular telecommunication system (Phase 2+); Radio transmission and reception".~~
- [7] ~~IEC 68-2: "Basic environmental testing procedures. Part 2 Tests".~~
- [8] ~~IEC 721: "Classification of environmental conditions".~~
- [9] ~~ETS 300 607-1 (GSM 11.10-1): "Digital cellular telecommunication system (Phase 2); Mobile Station (MS) conformance specification; Part 1: Conformance specification".~~
- [10] ~~ETS 300 609-1 (GSM 11.21): "Digital cellular telecommunication system (Phase 2); Base Station System (BSS) equipment specification, Part 1. Radio aspects".~~

1 Scope

The present document applies to the following radio equipment types:

1) Repeaters for GSM:

These radio equipment types are capable of operating in all or any part of the frequency bands given in table 1-1.

Table 1-1: GSM Repeater frequency bands

| | Direction of transmission | GSM Repeater frequency bands |
|-----------------|----------------------------------|-------------------------------------|
| <u>P-GSM900</u> | <u>Downlink</u> | <u>935 MHz to 960 MHz</u> |
| | <u>Uplink</u> | <u>890 MHz to 915 MHz</u> |
| <u>E-GSM900</u> | <u>Downlink</u> | <u>925 MHz to 960 MHz</u> |
| | <u>Uplink</u> | <u>880 MHz to 915 MHz</u> |
| <u>R-GSM900</u> | <u>Downlink</u> | <u>921 MHz to 960 MHz</u> |
| | <u>Uplink</u> | <u>876 MHz to 915 MHz</u> |
| <u>DCS1800</u> | <u>Downlink</u> | <u>1 805 MHz to 1 880 MHz</u> |
| | <u>Uplink</u> | <u>1 710 MHz to 1 785 MHz</u> |
| <u>GSM450</u> | <u>Downlink</u> | <u>460,4 MHz to 467,6 MHz</u> |
| | <u>Uplink</u> | <u>450,4 MHz to 457,6 MHz</u> |
| <u>GSM480</u> | <u>Downlink</u> | <u>488,8 MHz to 496 MHz</u> |
| | <u>Uplink</u> | <u>478,8 MHz to 486 MHz</u> |

NOTE: In some circumstances, for instance when an operator (or more than one operator who co-ordinate the use of repeaters), is not allocated a complete band as defined in table 1-1, it may be necessary to restrict the frequency range of operations of repeaters. In these circumstances, the test of "Gain outside operating band" in annex C may be used to verify the performance of the repeater.

The present document covers requirements for GSM Repeaters for Release 8.

The present document is intended to cover the provisions of Directive 1999/5/EC [i 2] (R&TTE Directive), article 3.2, which states that "radio equipment shall be so constructed that it effectively uses the spectrum allocated to terrestrial/space radio communications and orbital resources so as to avoid harmful interference".

In addition to the present document, other ENs that specify technical requirements in respect of essential requirements under other parts of article 3 of the R&TTE Directive [i 2] may apply to equipment within the scope of the present document.

NOTE: A list of such ENs is included on the web site <http://www.newapproach.org>.

2 References

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the reference document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found at <http://docbox.etsi.org/Reference>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication ETSI cannot guarantee their long term validity.

- [11] ~~ETR 027: "Methods of measurement for private mobile radio equipment".~~
- [12] ~~ETR 028: "Uncertainties in the measurement of mobile radio equipment characteristics".~~

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

broadband repeater: repeater which is designed for operation on any combination of ARFCNs (up to a specified maximum number) within the operating band of the ~~repeater~~.

channelized repeater: repeater which is designed for operation on a specified subset of ARFCNs within the operating band of the ~~repeater~~. The subset of ARFCNs may be determined during the manufacture of the repeater, or may be programmable.

~~repeater system using frequency shift: frequency shifting repeater consists of two different elements, a master unit close to the BTS and at least one remote unit close to the area to be covered. The master unit amplifies the channels from the BTS and shifts them to different GSM channels. In the remote unit the shifted channels from the master unit will be transferred back to the original channels and amplified. This is valid for the downlink signals as well as for the uplink signals. GSM. Unless otherwise specified, references to GSM include both GSM450, GSM 480, GSM 900 and DCS 1800.~~

repeater: bi-directional Radio Frequency (RF) amplifier which can amplify and transmit a received Mobile Station (MS) signal in the GSM MS transmit band, simultaneously it can amplify and transmit a received Base Transceiver Station (BTS) RF signal in the GSM BTS transmit band.

~~spurious emissions: emissions at frequencies other than those of the carrier and sidebands associated with normal modulation and switching.~~

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

| | |
|----------------|-------------------------------------|
| BTS | Base Transceiver Station |
| MS | Mobile Station |
| RF | Radio Frequency |

~~Abbreviations used within the GSM specifications are given in ETR 350 (GSM 01.04) [1].~~

4 General

~~A repeater can be designed to amplify the whole transmit RF band or just a part of the band. In the latter case the repeater can be either Broadband, with frequency band selective filtering, or channelized, with channel selective filtering.~~

4.1 Radio frequency bands

~~A repeater, as a bi-directional amplifier, can amplify and transmit a received MS signal in the MS transmit band, simultaneously it can amplify and transmit a received BTS signal in the BTS transmit band. The relevant MS and BTS transmit bands for the present document, which is a subset of the MS and BTS transmit bands as defined in GSM 05.05 [6], are given in table 1.~~

2.1 Normative references

The following referenced documents are necessary for the application of the present document.

- [1] [Void](#)
- [2] [ETSI TS 151 026 \(V8 3.0\): "Digital cellular telecommunications system \(Phase 2+\): Base Station System \(BSS\) equipment specification; Part 4: Repeaters \(3GPP TS 51 026 version 8 3 0 Release 8\)"](#)
- [3] [ETSI TS 151 021 \(V8 7.0\): "Digital cellular telecommunications system \(Phase 2+\): Base Station System \(BSS\) equipment specification; Radio aspects \(3GPP TS 51 021 version 8 7 0 Release 8\)"](#)
- [4] [ITU-R Recommendation SM 329-10 \(2003\): "Unwanted emissions in the spurious domain"](#)
- [5] [ETSI TS 151 010-1 \(V8 4.0\): "Digital cellular telecommunications system \(Phase 2+\): Mobile Station \(MS\) conformance specification; Part 1: Conformance specification \(3GPP TS 51 010-1 version 8 4 0 Release 8\)"](#)

2.2 Informative references

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

- [i.1] [Directive 98/34/EC of the European Parliament and of the Council of 22 June 1998 laying down a procedure for the provision of information in the field of technical standards and regulations](#)
- [i.2] [Directive 1999/5/EC of the European Parliament and of the Council of 9 March 1999 on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity \(R&TTE Directive\)](#)
- [i.3] [ETSI EG 201 399: "Electromagnetic compatibility and Radio spectrum Matters \(ERM\): A guide to the production of candidate Harmonized Standards for application under the R&TTE Directive"](#)
- [i.4] [ETSI TR 102 215 \(V1 3.1\): "Electromagnetic compatibility and Radio spectrum Matters \(ERM\): Recommended approach and possible limits for measurement uncertainty for the measurement of radiated electromagnetic fields above 1 GHz"](#)
- [i.5] [ETSI TR 100 028 \(all parts\) \(V1 4.1\): "Electromagnetic compatibility and Radio spectrum Matters \(ERM\): Uncertainties in the measurement of mobile radio equipment characteristics"](#)
- [i.6] [ETSI TS 145 005 \(V8 7.0\): "Digital cellular telecommunications system \(Phase 2+\): Radio Transmission and reception \(3GPP TS 45 005 version 8 7 0 Release 8\)"](#)

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

broadband repeater: repeater which is designed for operation on any combination of ARFCNs (up to a specified maximum number) within the operating band of the [repeater](#)

channelized repeater: repeater which is designed for operation on a specified subset of ARFCNs within the operating band of the [repeater](#)

NOTE: The subset of ARFCNs may be determined during the manufacture of the repeater, or may be programmable.

pass band: [repeater](#) can have one or several pass bands

~~Table 1. MS and BTS transmit RF bands~~

| | MS transmit band | BTS transmit band |
|----------------------|-----------------------------------|-----------------------------------|
| GSM 450 | 450,4 MHz to 457,0 MHz | 460,4 MHz to 467,0 MHz |
| GSM 480 | 478,8 MHz to 486,0 MHz | 488,8 MHz to 496,0 MHz |
| F-GSM 900 | 890 MHz to 915 MHz | 935 MHz to 960 MHz |
| E-GSM 900 | 880 MHz to 915 MHz | 925 MHz to 960 MHz |
| DCS 1800 | 1 710 MHz to 1 785 MHz | 1 805 MHz to 1 880 MHz |
| R-GSM 900 | 870 MHz to 915 MHz | 924 MHz to 960 MHz |

NOTE: In some circumstances, for instance when an operator (or more than one operator who co-ordinate the use of repeaters), is not allocated a complete band as defined in table 1, it may be necessary to restrict the frequency range of operations of repeaters. In these circumstances, the test of "Gain outside operating band" in annex A may be used to verify the performance of the repeater.

~~4.2 Test environments~~

For each test in the present document, the environmental conditions under which the repeater is to be tested are defined.

~~4.2.1 Normal test environment~~

When a normal test environment is specified for a test, the test should be performed under any combination of conditions between the minimum and maximum limits stated in table 2.

~~Table 2: Limits of conditions for Normal Test Environment~~

| Condition | Minimum | Maximum |
|--------------------------------|---|--------------------|
| Barometric pressure | 86 kPa | 106 kPa |
| Temperature | 15°C | 30°C |
| Relative Humidity | 20 % | 85 % |
| Power supply | Nominal, as declared by the manufacturer | |
| Vibration | Negligible | |

The ranges of barometric pressure, temperature and humidity represent the maximum variation expected in the uncontrolled environment of a test laboratory. If it is not possible to maintain these parameters within the specified limits, the actual values shall be recorded in the test report.

NOTE: This may, for instance, be the case for measurements of radiated emissions performed on an open field test site.

~~4.2.2 Extreme test environment~~

The manufacturer shall declare one of the following:

- ~~the equipment class for the equipment under test, as defined in ETS 300 019-1-3 [3];~~
- ~~the equipment class for the equipment under test, as defined in ETS 300 019-1-4 [4];~~
- ~~for equipment that does not comply to an ETS 300 019-1 [2] class, the relevant classes from IEC 721 [8] documentation for temperature, humidity and vibration shall be declared.~~

NOTE: Reduced functionality for conditions that fall outside of the standard operational conditions are not tested in the present document. These may be stated and tested separately.

~~4.2.3 Extreme temperature~~

When an extreme temperature test environment is specified for a test, the test shall be performed at the standard minimum and maximum operating temperatures defined by the manufacturer's declaration for the equipment under test.

repeater: bi-directional Radio Frequency (RF) amplifier which can amplify and transmit a received Mobile Station (MS) signal in the GSM MS transmit band, simultaneously it can amplify and transmit a radiated or conducted received Base Transceiver Station (BTS) RF signal in the GSM BTS transmit band

repeater system using frequency shift: repeater system consisting of two different elements, a master unit close to the BTS and at least one remote unit close to the area to be covered

NOTE: The master unit amplifies the channels from the BTS and shifts them to different GSM channels. In the remote unit the shifted channels from the master unit will be transferred back to the original channels and amplified. This is valid for the downlink signals as well as for the uplink signals.

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

| | |
|--------------|--|
| <u>ARECN</u> | <u>Absolute Radio Frequency Channel Number</u> |
| <u>BTS</u> | <u>Base Transceiver Station</u> |
| <u>EVM</u> | <u>Error Vector Magnitude</u> |
| <u>MS</u> | <u>Mobile Station</u> |
| <u>RF</u> | <u>Radio Frequency</u> |

4 Technical requirements specifications

4.1 Environmental profile

The technical requirements of the present document apply under the environmental profile for operation of the equipment, which shall be declared by the supplier. The equipment shall comply with all the technical requirements of the present document at all times when operating within the boundary limits of the declared operational environmental profile.

For guidance on how a supplier can declare the environmental profile, see annex B.

4.2 Conformance requirements

4.2.1 Conducted spurious emissions

4.2.1.1 Definition

This test measures the conducted spurious emissions at the antenna ports.

4.2.1.2 Limit

This requirement applies to all antenna ports of the repeater, at maximum gain, and with the following input signals:

- without any RF input signal;
- with a continuous sinusoidal RF signal at a level which will result, when measured, in the maximum rated RF output power per channel, as declared by the manufacturer RF input signal.

The measured power shall not exceed:

- -36 dBm (250 nW) in the frequency band 9 kHz to 1 GHz;
- -30 dBm (1µW) in the frequency band 1 GHz to 12,75 GHz.

~~Minimum temperature:~~

- ~~the test shall be performed with the environmental test equipment and methods of inducing the required environmental phenomena into the equipment, conforming to the test procedure of IEC 68-2-1 [7]. The equipment shall be maintained at the stabilized condition for the duration of the test sequence.~~

~~Maximum temperature:~~

- ~~the test shall be performed with the environmental test equipment and methods of inducing the required environmental phenomena into the equipment, conforming to the test procedure of IEC 68-2-2 [7]. The equipment shall be maintained at the stabilized condition for the duration of the test sequence.~~

~~NOTE: It is recommended that the equipment is made fully operational prior to the equipment being taken to its lower operating temperature.~~

~~4.3 Manufacturers declarations~~

~~The manufacturer shall declare:~~

- ~~the operating band or bands of the repeater,~~
- ~~the maximum rated output power per channel,~~
- ~~the number of channels supported by the repeater,~~
- ~~the supported modulation methods.~~

~~4.4 Methods of measurement~~

~~The general methods of measurement and measurement uncertainty shall be according to ETR 027 [11] and ETR 028 [12] except where they conflict with the present document.~~

~~5 Spurious emissions~~

~~5.1 Test purpose~~

~~This test measures the conducted spurious emissions (see clause 3.1) at the antenna ports and the effective power of spurious emissions radiated by the cabinet and structure.~~

~~5.2 Test case~~

~~The repeater shall be set to maximum gain. All measurement steps, as described in this clause, apply to all antenna ports of the repeater.~~

~~a) Spurious emissions from the antenna port:~~

- ~~one antenna port of the repeater shall be connected to a selective RF measurement device presenting to the repeater a load with an impedance of 50 Ω . An average power measurement of spurious emissions shall be performed for frequency offsets from the carrier frequency greater than 600 kHz under the following two conditions:~~
 - ~~without any RF input signal. The relevant input antenna port of the repeater shall be terminated with 50 Ω ;~~
 - ~~with an RF input signal. The relevant antenna input port of the repeater shall be connected to an RF signal generator. A continuous sinusoidal RF signal shall be input at a level which will result, when measured, in the maximum rated RF output power per channel, as declared by the manufacturer. The RF input signal shall be set to the centre frequency of the repeaters operating band. In the case of a channelized repeater,~~

Table 4.2.1.2-1: Measurement bandwidth for spurious emissions

| Band | Frequency offset (offset from carrier) | Measurement bandwidth |
|--|--|--|
| <u>In the relevant BTS transmit Band or MS transmit band</u> | <u>≥ 100 kHz</u> | <u>3 kHz</u> |
| <u>100 kHz to 50 MHz</u> | <u>=</u> | <u>10 kHz</u> |
| <u>50 MHz to 500 MHz outside the relevant transmit band</u> | <u>(offset from edge of the relevant transmit band)</u> <u>> 0 MHz</u> <u>≥ 2 MHz</u> <u>≥ 5 MHz</u> | <u>10 kHz</u> <u>30 kHz</u> <u>100 kHz</u> |
| <u>Above 500 MHz outside the relevant transmit band</u> | <u>(offset from edge of the relevant transmit band)</u> <u>> 0 MHz</u> <u>≥ 2 MHz</u> <u>≥ 5 MHz</u> <u>≥ 10 MHz</u> <u>≥ 20 MHz</u> <u>≥ 30 MHz</u> | <u>10 kHz</u> <u>30 kHz</u> <u>100 kHz</u> <u>300 kHz</u> <u>1 MHz</u> <u>3 MHz</u> |

4.2.1.3 Conformance

Conformance tests described in clause 5.3.1 shall be carried out.

4.2.2 Radiated spurious emissions

4.2.2.1 Definition

This test measures the effective power of spurious emissions radiated by the cabinet and structure.

4.2.2.2 Limit

This requirement applies to all antenna ports of the repeater, at maximum gain, and with the following input signals:

- without any RF input signal;
- with a continuous sinusoidal RF signal at a level which will result, when measured, in the maximum rated RF output power per channel, as declared by the manufacturer RF input signal.

The effective radiated power shall not exceed:

- -36 dBm (250 nW) in the frequency band 30 MHz to 1 GHz;
- -30 dBm (1µW) in the frequency band 1 GHz to 12,75 GHz.

the RF input signal shall be set to the centre of the supported ARFCN closest to the centre of the range of ARFCNs supported by the repeater.

~~b) Radiated spurious emissions:~~

- ~~a test site fulfilling the requirements of ETS 300 113 [5] shall be used, except when it conflicts with the present document. The repeater shall be placed on a non-conducting support and shall be operated from a power source as recommended by the manufacturer via an RF filter, to prevent the power source or cable from influencing the result of the measurement;~~
- ~~the relevant output antenna port of the repeater shall be terminated with 50 ohms. The relevant antenna input port of the repeater shall be connected to a RF signal generator in such a way that the connection does not influence the result of the measurement. The RF input signal shall be set to the centre frequency of the repeaters operating band. A continuous sinusoidal RF signal shall be input at a level which will result, when measured, in the maximum rated output power per channel, as declared by the manufacturer.~~
- ~~an average RF power measurement shall be performed for frequency offsets from the carrier frequency greater than 600 kHz over the frequency range 30 MHz to 4 GHz. The repeater shall be rotated through 360° in the horizontal plane and the test antenna shall be raised or lowered until the maximum spurious signal level is detected. The effective radiated power of each spurious component shall be determined by a substitution measurement;~~
- ~~the measurements shall be repeated with orthogonal polarization of the test antenna;~~
- ~~the measurements shall be repeated with no RF input signal, in this case the relevant antenna input port of the repeater shall be terminated with 50 ohms.~~

Table 3: Measurement bandwidth for spurious emissions

| Band | Frequency offset (offset from carrier) | Measurement bandwidth |
|---|--|-----------------------|
| In the relevant BTS transmit Band or MS transmit band | ≥ 100 kHz | 3 kHz |
| 100 kHz to 50 MHz | : | 10 kHz |
| 50 MHz to 500 MHz outside the relevant transmit band | (offset from edge of the relevant transmit band) | |
| | > 0 MHz | 10 kHz |
| | ≥ 2 MHz | 30 kHz |
| | ≥ 5 MHz | 100 kHz |
| Above 500 MHz outside the Relevant transmit band | (offset from edge of the relevant transmit band) | |
| | > 0 MHz | 10 kHz |
| | ≥ 2 MHz | 30 kHz |
| | ≥ 5 MHz | 100 kHz |
| | ≥ 10 MHz | 300 kHz |
| | ≥ 20 MHz | 1 MHz |
| | ≥ 30 MHz | 3 MHz |

~~Test environment:~~ Normal

~~5.3 Conformance requirement~~

~~The measured power in test case clause 5.2.a) as well as the effective radiated power in test case clause 5.2.b) shall not exceed:~~

- -36 dBm (250 nW) in the frequency band ~~9 kHz to 1 GHz,~~
- -30 dBm (1µW) in the frequency band 1 GHz to 12,75 GHz.

Table 4.2.2.2-1: Measurement bandwidth for spurious emissions

| Band | Frequency offset (offset from carrier) | Measurement bandwidth |
|---|---|--|
| In the relevant BTS transmit Band or MS transmit band | ≤ 100 kHz | 3 kHz |
| 30 MHz to 50 MHz | ↓ | 10 kHz |
| 50 MHz to 500 MHz outside the relevant transmit band | (offset from edge of the relevant transmit band) > 0 MHz ≤ 2 MHz ≤ 5 MHz | 10 kHz 30 kHz 100 kHz |
| Above 500 MHz outside the relevant transmit band | (offset from edge of the relevant transmit band) > 0 MHz ≤ 2 MHz ≤ 5 MHz ≤ 10 MHz ≤ 20 MHz ≤ 30 MHz | 10 kHz 30 kHz 100 kHz 300 kHz 1 MHz 3 MHz |

4.2.2.3 Conformance

Conformance tests described in clause 5.3.2 shall be carried out.

4.2.3 Intermodulation attenuation

4.2.3.1 Definition

To verify that the level of intermodulation products, generated in non-linear elements of the repeater, in the presence of two RF input signals, do not exceed the specified limits.

4.2.3.2 Limit

This requirement applies to all antenna ports of the repeater, at maximum gain, and with the following input signals:

- with a continuous sinusoidal RF signal at a level which will result, when measured, in the maximum rated RF output power per channel, as declared by the manufacturer RF input signal;
- with 10 dB increased continuous sinusoidal RF signals compared to the continuous sinusoidal RF signal at a level which will result, when measured, in the maximum rated RF output power per channel, as declared by the manufacturer RF input signal.

The maximum level of intermodulation product shall be not greater than:

- -36 dBm (250 nW) in the frequency band 9 kHz to 1 GHz;
- -30 dBm (1 μW) in the frequency band 1 GHz to 12,75 GHz.

4.2.3.3 Conformance

Conformance tests described in clause 5.3.3 shall be carried out.

4.2.4 Out-of-band gain

4.2.4.1 Definition

To test the net gain of the repeater outside the relevant MS or BTS transmit band.

This test shall also check the net gain at harmonic frequencies.

~~5.4 Reference requirement~~

~~GSM 05.05 [6], annex E.~~

~~6 Intermodulation attenuation~~

~~6.1 Test purpose~~

To verify that the level of intermodulation products, generated in non-linear elements of the repeater, in the presence of two RF input signals, do not exceed the specified limits.

~~6.2 Test case~~

The repeater shall be set to maximum gain. Two continuous sinusoidal RF signals shall be fed to the input antenna port of the repeater using a combining device. The frequencies of both RF signals shall be within the repeater's ~~operating~~ band. The spacing between both RF signals shall be the minimum possible spacing applied in a network, i.e. 600 kHz.

The level of both RF input signals shall be increased, until the maximum rated output power per channel, as declared by the manufacturer, is reached.

In case of a repeater only supporting one channel, one RF input signal shall be set to the operating frequency and the other RF input signal at an offset of 400 kHz to either side successively. In this case the input signal at the repeaters operating frequency shall be increased, until the maximum rated output power per channel, as declared by the manufacturer, is reached. The second signal shall be set to the same input level.

The level of the third order intermodulation products shall be measured by means of a selective measurement device presenting to the repeater a load with an impedance of 50 ~~ohms~~.

The test shall be repeated with both RF input signals increased by 10 dB each.

NOTE: In this case, the automatic gain (level) control may reduce the gain to a value less than maximum gain in order to keep the maximum rated output power per channel, as declared by the manufacturer.

An average power measurement shall be performed using a bandwidth of 3 kHz.

The measurements shall apply to all antenna ports of the repeater.

~~Test environment:~~ Normal

~~6.3 Conformance requirement~~

The maximum level of intermodulation product shall be not greater than:

— 36 dBm (250 nW) in the frequency band 9 kHz to 1 GHz;

! 30 dBm (1 μW) in the frequency band 1 GHz to 12,75 GHz.

~~6.4 Reference requirement~~

~~GSM 05.05 [6] annex E.~~

4.2.4.2 Limit

This requirement applies to all antenna ports of the repeater, at maximum gain.

The net gain in both directions through the repeater shall be less than:

- 50 dB at 400 kHz offset and greater;
- 40 dB at 600 kHz offset and greater;
- 35 dB at 1 MHz offset and greater;
- 25 dB at 5 MHz offset and greater;

from the edges of the relevant MS or BTS transmit bands.

4.2.4.3 Conformance

Conformance tests described in clause 5.3.4 shall be carried out.

4.2.5 Frequency error

4.2.5.1 Definition

This clause applies only to repeater systems using frequency shift and describes the test of the frequency error.

4.2.5.2 Limit

The average frequency error of the repeater system shall not exceed 0,1 ppm.

If tested, the average frequency error of a single repeater shall not exceed 0,05 ppm.

4.2.5.3 Conformance

Conformance tests described in clause 5.3.5 shall be carried out.

4.2.6 Modulation accuracy at GMSK modulation

4.2.6.1 Definition

This clause applies only to repeater systems using frequency shift and describes the test of the phase error.

4.2.6.2 Limit

The phase error of a complete repeater system shall not exceed:

- 7° rms;
- 28° peak.

If tested, the phase error of a single repeater unit shall not exceed:

- 6,1° rms;
- 24,5° peak.

4.2.6.3 Conformance

Conformance tests described in clause 5.3.6 shall be carried out.

~~7 Out of band gain~~

~~7.1 Test purpose~~

To test the net gain of the repeater outside the relevant MS or BTS transmit band. This test shall also check the net gain at harmonic frequencies.

~~7.2 Test case~~

The repeater shall be set to maximum gain. In case of a channel selective repeater, two of the channel selective modules shall be set to the lowermost and the uppermost ARFCN within the repeater's ~~operating~~ band.

A continuous sinusoidal RF signal shall be fed successively at frequency offsets Y from the edges of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater. The frequency offsets Y shall have the following values:

~~400 kHz, 600 kHz, 800 kHz, 1 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz.~~

This shall be repeated with an RF input signal successively set to all harmonic frequencies of the repeaters ~~operating~~ band up to 12,75 GHz (i.e. multiples of the centre frequency of the repeaters ~~operating~~ band up to 12,75 GHz).

The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the ~~operating~~ band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

The average output power in each case shall be measured and the net gain shall be recorded.

The measurements shall apply to all antenna ports of the repeater.

~~Test environment:~~ Normal
 Extreme temperature

~~7.3 Conformance requirement~~

The net gain in both directions through the repeater shall be less than:

- 50 dB at 400 kHz offset and greater;
- 40 dB at 600 kHz offset and greater;
- ~~- 35 dB at 1 MHz offset and greater;~~
- ~~- 25 dB at 5 MHz offset and greater;~~

~~from the edges of the relevant MS or BTS transmit bands.~~

~~7.4 Reference requirement~~

~~GSM 05.05 [6], annex E.~~

~~8 Frequency error~~

~~8.1 Test purpose~~

~~This clause applies only to repeater systems using frequency shift and describes the test of the frequency error.~~

4.2.7 Modulation accuracy at 8-PSK, QPSK, 16-QAM or 32-QAM modulation

4.2.7.1 Definition

This clause applies only to repeater systems supporting 8-PSK, QPSK, 16-QAM or 32-QAM modulation and describes the test of the modulation accuracy.

4.2.7.2 Limit

For a repeater as defined in the first column of the table 4.2.7.2-1 the RMS EVM shall not exceed

Table 4.2.7.2-1: Modulation accuracy at 8-PSK, QPSK, 16-QAM or 32-QAM modulation

| | | <u>Normal symbol rate</u> | | | <u>Higher symbol rate</u> | | |
|--|---------------------------------|---------------------------|---------------|---------------|---------------------------|---------------|---------------|
| | | <u>8-PSK</u> | <u>16-QAM</u> | <u>32-QAM</u> | <u>QPSK</u> | <u>16-QAM</u> | <u>32-QAM</u> |
| <u>For a single repeater with no shift in frequency from input to output</u> | <u>under normal conditions</u> | <u>8,0 %</u> | <u>4,0 %</u> | <u>4,0 %</u> | <u>8,0 %</u> | <u>4,0 %</u> | <u>4,0 %</u> |
| <u>For a single repeater with no shift in frequency from input to output</u> | <u>under extreme conditions</u> | <u>8,0 %</u> | <u>5,0 %</u> | <u>5,0 %</u> | <u>8,0 %</u> | <u>5,0 %</u> | <u>5,0 %</u> |
| <u>For a complete repeater system using frequency shift</u> | <u>under normal conditions</u> | <u>11 %</u> | <u>6,0 %</u> | <u>6,0 %</u> | <u>11 %</u> | <u>6,0 %</u> | <u>6,0 %</u> |
| <u>For a complete repeater system using frequency shift</u> | <u>under extreme conditions</u> | <u>11 %</u> | <u>7,0 %</u> | <u>7,0 %</u> | <u>11 %</u> | <u>7,0 %</u> | <u>7,0 %</u> |

4.2.7.3 Conformance

Conformance tests described in clause 5.3.7 shall be carried out.

5 Testing for compliance with technical requirements

5.1 Environmental conditions for testing

Tests defined in the present document shall be carried out at representative points within the boundary limits of the declared operational environmental profile.

Where technical performance varies subject to environmental conditions, tests shall be carried out under a sufficient variety of environmental conditions (within the boundary limits of the declared operational environmental profile) to give confidence of compliance for the affected technical requirements.

5.2 Interpretation of the measurement results

The interpretation of the results recorded in a test report for the measurements described in the present document shall be as follows:

- the measured value related to the corresponding limit will be used to decide whether an equipment meets the requirements of the present document;
- the value of the measurement uncertainty for the measurement of each parameter shall be included in the test report;
- the recorded value of the measurement uncertainty shall be, for each measurement, equal to or lower than the figures in table 5.2.1.

~~8.2 Test case~~

The repeater system shall be levelled according to the recommendations of the manufacturer. For the purpose of the frequency synchronisation of the repeater system it might be necessary to connect the system to a BTS or an equivalent test equipment like a mobile tester. In all cases an accurate frequency synchronisation source has to be used to synchronise the measurement setup.

The test of the repeater system shall be performed at the lowest and the highest ARFCN supported by the repeater system. For the measurement of the frequency error a continuous, sinusoidal and synchronised RF signal shall be fed successively at a frequency of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater. The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the ~~operating~~ band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

The average output frequency shall be measured with a frequency counter.

The frequency error of single elements within the repeater system such as master unit or remote unit may be measured as well.

~~Test environment:~~ ~~Normal~~
 ~~Extreme temperature~~

~~8.3 Conformance requirement~~

~~The average frequency error of the repeater system shall not exceed 0,1 ppm. If tested, the average frequency error of a single repeater shall not exceed 0,05 ppm.~~

~~8.4 Reference requirement~~

~~GSM 05.05 [6], annex E.~~

~~9 Modulation accuracy at GMSK modulation~~

~~9.1 Test purpose~~

~~This clause applies only to repeater systems using frequency shift and describes the test of the phase error.~~

~~9.2 Test case~~

The repeater system shall be levelled according to the recommendations of the manufacturer. For the purpose of the frequency synchronisation of the repeater system it might be necessary to connect the system to a BTS or an equivalent test equipment like a mobile tester. In all cases an accurate frequency synchronisation source has to be used to synchronise the measurement setup.

For the measurement of the phase error a continuous and synchronised GMSK signal modulated with a pseudo random bit sequence shall be fed successively at one frequency of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater. The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the ~~operating~~ band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

The phase trajectory shall be measured at the equivalent output of the repeater system and the calculation of the phase error shall be performed according to ~~GSM 11.10-1 [9] or GSM 11.21 [10]~~.

~~The phase error of single elements within the repeater system such as master unit or remote unit may be measured as well.~~

For the test methods, according to the present document, the measurement uncertainty figures shall be calculated and shall correspond to an expansion factor (coverage factor) $k = 1,96$ or $k = 2$ (which provide confidence levels of respectively 95 % and 95,45 % in the case where the distributions characterising the actual measurement uncertainties are normal (Gaussian)). Principles for the calculation of measurement uncertainty are contained in TR 100 028 [i 5] or TR 102 215 [i 4].

Table 5 2-1 is based on such expansion factors.

Table 5 2-1: Maximum measurement uncertainty

| Parameter | Condition | Uncertainty |
|--|---|---|
| Conducted spurious emissions | inside the BTS transmit band or MS transmit band | $\pm 1,5$ dB |
| | in the receive band of the BSS | ± 3 dB |
| | elsewhere $f < 2,2$ GHz $2,2$ GHz $< f < 4$ GHz $f > 4$ GHz | $\pm 1,5$ dB $\pm 2,0$ dB $\pm 4,0$ dB |
| Radiated spurious emissions | RF power | $\pm 6,0$ dB |
| Intermodulation attenuation | Formula: $\sqrt{(CW1_level_error)^2 + (2 \times CW2_level_error)^2 + (measurement_error)^2}$ RSS: CW1 level error, 2 x CW2 level error, and measurement error (using all errors = $\pm 0,5$ dB) | $\pm 1,2$ dB |
| Out-of-band gain | Calibration of test set-up shall be made without DUT in order to achieve the accuracy | $\pm 0,5$ dB |
| Frequency error | Frequency | ± 10 Hz (+ 5 Hz for GSM 400) |
| Modulation accuracy at GMSK modulation | Phase | $1,5^\circ$ rms; 5° peak |
| Modulation accuracy at 8-PSK, QPSK, 16-QAM or 32-QAM modulation | EVM | 2 % Stimulus $\pm (0,75 + 0,025 \text{ RMS_EVM}) = \pm (0,75 + 0,025 \text{ RMV_EVM}) \% \text{ RMS}$ |

5.3 Essential radio test suites

5.3.1 Conducted spurious emissions

5.3.1.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.

- 1) One antenna port of the repeater shall be connected to a selective RF measurement device presenting to the repeater a load with an impedance of 50Ω .

5.3.1.2 Procedures

- 1) An average power measurement of spurious emissions shall be performed for frequency offsets from the carrier frequency greater than 600 kHz, with a measurement bandwidth according to table 4.2.2.2-1, without any RF input signal. The relevant input antenna port of the repeater shall be terminated with 50Ω .
- 2) An average power measurement of spurious emissions shall be performed for frequency offsets from the carrier frequency greater than 600 kHz, with a measurement bandwidth according to table 4.2.2.2-1, with an RF input signal. The relevant antenna input port of the repeater shall be connected to an RF signal generator. A continuous sinusoidal RF signal shall be input at a level which will result, when measured, in the maximum rated RF output power per channel, as declared by the manufacturer. The RF input signal shall be set to the centre frequency of the repeaters pass band. In the case of a channelized repeater, the RF input signal shall be set to the centre of the supported ARFCN closest to the centre of the range of ARFCNs supported by the repeater.

~~The GMSK signal source shall have a phase error below the following values:~~

~~5 degrees rms;~~

~~20 degrees peak.~~

~~Test environment: Normal
 Extreme temperature~~

~~9.3 Conformance requirement~~

~~The phase error of a complete repeater system shall not exceed:~~

~~7 degrees rms;~~

~~28 degrees peak.~~

~~If tested, the phase error of a single repeater unit shall not exceed:~~

~~6.1 degrees rms;~~

~~24.5 degrees peak.~~

~~9.4 Reference requirement~~

~~GSM 05.05 [6], annex E.~~

~~10 Modulation accuracy at 8-PSK modulation~~

~~10.1 Test purpose~~

~~This clause applies only to repeater systems supporting 8-PSK modulation and describes the test of the modulation accuracy.~~

~~10.2 Test case~~

The repeater system shall be levelled according to the recommendations of the manufacturer. For the purpose of the frequency synchronisation of the repeater system it might be necessary to connect the system to a BTS or an equivalent test equipment like a mobile tester. In all cases an accurate frequency synchronisation source has to be used to synchronise the measurement setup.

For the measurement of the modulation accuracy a continuous and synchronised 8-~~PSK~~ signal modulated with a pseudo random bit sequence shall be fed successively at one frequency of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater. The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the ~~operating~~ band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

The EVM shall be measured at the equivalent output of the repeater system and the calculation of the EVM shall be performed according to ~~GSM 11.21 [10]~~.

~~The modulation accuracy of single elements within the frequency shifting repeater system such as master unit or remote unit may be measured as well:~~

~~Test environment: Normal
 Extreme temperature~~

The results obtained shall be compared to the limits in clause 4.2.1.2 in order to prove compliance.

5.3.2 Radiated spurious emissions

5.3.2.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.

- 1) A test site fulfilling the requirements of ITU-R Recommendation SM 329 [4] shall be used, except when it conflicts with the present document. The repeater shall be placed on a non-conducting support and shall be operated from a power source as recommended by the manufacturer via an RF filter, to prevent the power source or cable from influencing the result of the measurement.

5.3.2.2 Procedures

- 1) The relevant output antenna port of the repeater shall be terminated with 50 Ω . The relevant antenna input port of the repeater shall be connected to a RF signal generator in such a way that the connection does not influence the result of the measurement. The RF input signal shall be set to the centre frequency of the repeaters pass band. A continuous sinusoidal RF signal shall be input at a level which will result, when measured, in the maximum rated output power per channel, as declared by the manufacturer.
- 2) An average RF power measurement shall be performed for frequency offsets from the carrier frequency greater than 600 kHz over the frequency range 30 MHz to 12.75 GHz, with a measurement bandwidth according to table 4.2.2.1. The repeater shall be rotated through 360° in the horizontal plane and the test antenna shall be raised or lowered until the maximum spurious signal level is detected. The effective radiated power of each spurious component shall be determined by a substitution measurement.
- 3) The measurements shall be repeated with orthogonal polarization of the test antenna.
- 4) The measurements shall be repeated with no RF input signal, in this case the relevant antenna input port of the repeater shall be terminated with 50 Ω .

The results obtained shall be compared to the limits in clause 4.2.2.2 in order to prove compliance.

5.3.3 Intermodulation attenuation

5.3.3.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.

5.3.3.2 Procedures

- 1) The repeater shall be set to maximum gain.
- 2) Two continuous sinusoidal RF signals shall be fed to the input antenna port of the repeater using a combining device. The frequencies of both RF signals shall be within the repeater's pass band. The spacing between both RF signals shall be the minimum possible spacing applied in a network, i.e. 600 kHz.

The level of both RF input signals shall be increased, until the maximum rated output power per channel, as declared by the manufacturer, is reached.

In case of a repeater only supporting one channel, one RF input signal shall be set to the operating frequency and the other RF input signal at an offset of 400 kHz to either side successively. In this case the input signal at the repeaters operating frequency shall be increased, until the maximum rated output power per channel, as declared by the manufacturer, is reached. The second signal shall be set to the same input level.

- 3) The level of the third order intermodulation products shall be measured by means of a selective measurement device presenting to the repeater a load with an impedance of 50 Ω .

An average power measurement shall be performed using a bandwidth of 3 kHz.

~~10.3 Conformance requirement~~

~~For a single repeater with no shift in frequency the EVM shall not exceed:~~

~~- 8 % RMS.~~

~~For a complete repeater system using frequency shift the EVM shall not exceed:~~

~~- 14,5 % RMS.~~

~~If tested, the EVM of a single repeater unit in a frequency shifting repeater system shall not exceed:~~

~~- 12 % RMS.~~

~~10.4 Reference requirement~~

~~GSM 05.05 [6], annex E.~~

- 4) The test shall be repeated with both RF input signals increased by 10 dB each.

NOTE: In this case, the automatic gain (level) control may reduce the gain to a value less than maximum gain in order to keep the maximum rated output power per channel, as declared by the manufacturer.

- 5) The measurements shall apply to all antenna ports of the repeater.

The results obtained shall be compared to the limits in clause 4.2.3.2 in order to prove compliance.

5.3.4 Out-of-band gain

5.3.4.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.
extreme temperature, see TS 151 026 [2], clause 4.2.3.

5.3.4.2 Procedures

- 1) The repeater shall be set to maximum gain.

In case of a channel selective repeater, two of the channel selective modules shall be set to the lowermost and the uppermost ARFCN within the repeater's pass band.

- 2) A continuous sinusoidal RF signal shall be fed successively at frequency offsets Y from the edges of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater.

The frequency offsets Y shall have the following values:

- 400 kHz;
- 600 kHz;
- 800 kHz;
- 1 MHz;
- 5 MHz;
- 10 MHz;
- 15 MHz;
- 20 MHz.

The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the pass band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

- 3) The average output power in each case shall be measured and the net gain shall be recorded.
- 4) This shall be repeated with an RF input signal successively set to all harmonic frequencies of the repeaters pass band up to 12,75 GHz (i.e. multiples of the centre frequency of the repeaters pass band up to 12,75 GHz).
- 5) The measurements shall apply to all antenna ports of the repeater.

The results obtained shall be compared to the limits in clause 4.2.4.2 in order to prove compliance.

~~Annex A~~ (informative): Testing of gain for part band repeaters

~~A.1~~ Rationale for this test

The normative provisions of the present document specify the out-of band gain relative to the edge of one of the GSM bands specified in clause 4.1. The purpose of this informative annex is to define a test method which may be used to measure the out-of-band gain for a repeater which is designed to operate only over part of one of these bands. This test may be used for acceptance testing or for regulatory purposes.

~~Since GSM 05-05 does not specify the out-of-band gain requirements within a GSM band for a such a repeater, the performance requirements for the repeater must be agreed prior to this test being performed.~~ Normally, the requirements for the uplink and downlink directions will be similar, but with the frequencies offset by 45 MHz or 95 MHz.

~~A.2~~ ~~Gain outside operating band~~

~~A.2.1~~ Test purpose

To determine the net gain of the repeater outside its specified ~~operating~~ band (or bands), when this is less than a GSM band defined in clause 4.1 of the present document. ~~The requirements of clause 7 of the present document shall always be met,~~ whether or not this test is also performed.

This test is not a normative requirement of the present document.

~~A.2.2~~ ~~Test case~~

~~The repeater shall be set to maximum gain. In case of a channel selective repeater, two of the channel selective modules shall be set to the lowermost and the uppermost ARFCN within the repeaters operating band.~~

~~A continuous sinusoidal RF signal shall be fed successively at each specified frequency into the relevant input port of the repeater. The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the specified operating band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.~~

~~The average output power in each case shall be measured and the net gain shall be recorded.~~

~~The measurements shall apply to all antenna ports of the repeater.~~

Test environment: ~~Normal~~
~~Extreme temperature~~

~~A.2.3~~ ~~Conformance requirement~~

~~At each frequency specified to be measured, the gain through the repeater shall be less than the specified value.~~

5.3.5 Frequency error

5.3.5.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.
extreme temperature, see TS 151 026 [2], clause 4.2.3.

- 1) The repeater system shall be levelled according to the recommendations of the manufacturer. For the purpose of the frequency synchronisation of the repeater system it might be necessary to connect the system to a BTS or an equivalent test equipment like a mobile tester. In all cases an accurate frequency synchronisation source has to be used to synchronise the measurement setup.

5.3.5.2 Procedures

- 1) The test of the repeater system shall be performed at the lowest and the highest ARFCN supported by the repeater system.

For the measurement of the frequency error a continuous, sinusoidal and synchronised RF signal shall be fed successively at a frequency of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater.

The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the **pass** band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

- 2) The average output frequency shall be measured with a frequency counter.
- 3) The frequency error of single elements within the repeater system such as master unit or remote unit may be measured as well.

The results obtained shall be compared to the limits in clause 4.2.5.2 in order to prove compliance.

5.3.6 Modulation accuracy at GMSK modulation

5.3.6.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.
extreme temperature, see TS 151 026 [2], clause 4.2.3.

- 1) The repeater system shall be levelled according to the recommendations of the manufacturer. For the purpose of the frequency synchronisation of the repeater system it might be necessary to connect the system to a BTS or an equivalent test equipment like a mobile tester. In all cases an accurate frequency synchronisation source has to be used to synchronise the measurement setup.

- 2) **The GMSK signal source shall have a phase error below the following values:**

• **5° rms;**

• **20° peak.**

5.3.6.2 Procedures

- 1) For the measurement of the phase error a continuous and synchronised GMSK signal modulated with a pseudo random bit sequence shall be fed successively at one frequency of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater.

The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the **pass** band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

- 2) The phase trajectory shall be measured at the equivalent output of the repeater system and the calculation of the phase error shall be performed according to TS 151 010-1 [5] or TS 151 021 [3].

~~Annex B (informative): Change history~~

~~This annex lists all change requests approved for the present document since the first phase 2 version was approved by ETSI SMG.~~

| SMGW | SMG tdoc | SMGS tdoc | VERG | GR | RV | PH | GAT | SUBJECT | Resulting Version |
|-----------------|---------------------|----------------------|------------------|-----------------|---------------|----------------|----------------|--|------------------------------|
| G17 | 005/06 | | 4.0.0 | 004 | | 2 | D | Editorial additions and changes to comply with ETSI style | 4.1.0 |
| | 005/06 | | 4.0.0 | 002 | | 2 | D | Addition of definition of normal and extreme conditions for testing | 4.1.0 |
| | 005/06 | | 4.0.0 | 003 | | 2 | | Definition of test method for part band repeaters | 4.1.0 |
| G10 | 257/06 | | 4.1.0 | A004 | | 2 | F | Intermodulation attenuation | 4.2.0 |
| G20 | 606/06 | 50/06 | 4.2.0 | A005 | | 2 | D | Correction of reference title | 4.2.1 |
| G20 | 703/07 | 004/07 | 4.2.2 | A006 | | R06 | D | Addition of references to the R-GSM band | 5.0.0 |
| G25 | 00-0408 | 00p007 | 5.0.1 | A007 | | R06 | F | Minimum offset for spurious emissions measurements | 5.1.0 |
| S20 | 90-995 | 90p051 | 5.1.0 | A008 | | R90 | D | Repeater systems using frequency shift | 5.2.0 |
| S20 | 90-995 | 90p050 | 5.1.0 | A009 | | R90 | D | Addition of reference to ETR 027 and ETR 028 | 5.2.0 |
| | | | 5.2.0 | | | | | Version update for publication | 5.2.1 |
| S41b | F-00-190 | 006/06 | 5.2.1 | A011 | 2 | R99 | D | Repeater EDGE & GSM 400 test cases | 6.0.0 |
| | | | 6.0.1 | | | | | Update to Version 6.0.2 for Publication | 6.0.2 |

The results obtained shall be compared to the limits in clause 4.2.6.2 in order to prove compliance.

5.3.7 Modulation accuracy at 8-PSK, QPSK, 16-QAM or 32-QAM modulation

5.3.7.1 Initial conditions

Test environment: normal, see TS 151 026 [2], clause 4.2.1.
extreme temperature, see TS 151 026 [2], clause 4.2.3.

- 1) The repeater system shall be levelled according to the recommendations of the manufacturer. For the purpose of the frequency synchronisation of the repeater system it might be necessary to connect the system to a BTS or an equivalent test equipment like a mobile tester. In all cases an accurate frequency synchronisation source has to be used to synchronise the measurement setup.

5.3.7.2 Procedures

- 1) For the measurement of the modulation accuracy a continuous and synchronised 8-PSK, QPSK, 16-QAM or 32-QAM signal modulated with a pseudo random bit sequence shall be fed successively at one frequency of the relevant MS or BTS transmit frequency band into the relevant input port of the repeater.

The power level of the RF input signal shall be at least 5 dB below the power level which would produce, when applied within the pass band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

- 2) The EVM shall be measured at the equivalent output of the repeater system and the calculation of the EVM shall be performed according to TS 151 021 [3].

The results obtained shall be compared to the limits in clause 4.2.7.2 in order to prove compliance.

~~History~~

| Document history | | |
|-----------------------------|-------------------------|--|
| V8.0.1 | May 2000 | One-step Approval Procedure GAP 20000922. 2000-05-24 to 2000-09-22 |
| V8.0.2 | October 2000 | Publication |
| | | |
| | | |
| | | |

Annex A (normative):

HS Requirements and conformance Test specifications

Table (HS-RTT)

The HS Requirements and conformance Test specifications Table (HS-RTT) in table A 1 serves a number of purposes, as follows:

- it provides a statement of all the requirements in words and by cross reference to (a) specific clause(s) in the present document or to (a) specific clause(s) in (a) specific referenced document(s);
- it provides a statement of all the test procedures corresponding to those requirements by cross reference to (a) specific clause(s) in the present document or to (a) specific clause(s) in (a) specific referenced document(s);
- it qualifies each requirement to be either:
 - Unconditional: meaning that the requirement applies in all circumstances; or
 - Conditional: meaning that the requirement is dependent on the manufacturer having chosen to support optional functionality defined within the schedule;
- in the case of Conditional requirements, it associates the requirement with the particular optional service or functionality;
- it qualifies each test procedure to be either:
 - Essential: meaning that it is included with the Essential Radio Test Suite and therefore the requirement shall be demonstrated to be met in accordance with the referenced procedures;
 - Other: meaning that the test procedure is illustrative but other means of demonstrating compliance with the requirement are permitted.

Table A 1- HS Requirements and conformance Test specifications Table (HS-RTT)

| Harmonized Standard EN 300 609-4 | | | | | | |
|--|--|---------------------------------|-----------------------------------|--|---------------------------|---------------------------------|
| <u>The following requirements and test specifications are relevant to the presumption of conformity under the article 3.2 of the R&TTE Directive</u> | | | | | | |
| Requirement | | | Requirement Conditionality | | Test Specification | |
| No | Description | Reference- Clause No | U/C | Condition | E/O | Reference- Clause No |
| 1 | <u>Conducted spurious emissions</u> | <u>4.2.1</u> | <u>U</u> | | <u>E</u> | <u>5.3.1</u> |
| 2 | <u>Radiated spurious emission</u> | <u>4.2.2</u> | <u>U</u> | | <u>E</u> | <u>5.3.2</u> |
| 3 | <u>Intermodulation attenuation</u> | <u>4.2.3</u> | <u>U</u> | | <u>E</u> | <u>5.3.3</u> |
| 4 | <u>Out-of-band gain</u> | <u>4.2.4</u> | <u>U</u> | | <u>E</u> | <u>5.3.4</u> |
| 5 | <u>Frequency error</u> | <u>4.2.5</u> | <u>C</u> | <u>Only for Repeater systems using frequency shift</u> | <u>E</u> | <u>5.3.5</u> |
| 6 | <u>Modulation accuracy at GMSK modulation</u> | <u>4.2.6</u> | <u>C</u> | <u>Only for Repeater systems using frequency shift</u> | <u>E</u> | <u>5.3.6</u> |
| 7 | <u>Modulation accuracy at 8-PSK modulation</u> | <u>4.2.7</u> | <u>C</u> | <u>Only for Repeater systems supporting 8-PSK</u> | <u>E</u> | <u>5.3.7</u> |

Key to columns:

Requirement:

No A unique identifier for one row of the table which may be used to identify a requirement or its test specification.

Description A textual reference to the requirement.

Clause Number Identification of clause(s) defining the requirement in the present document unless another document is referenced explicitly

Requirement Conditionality:

I/C Indicates whether the requirement is to be *unconditionally* applicable (I) or is *conditional upon the manufacturer's claimed functionality of the equipment* (C)

Condition Explains the conditions when the requirement shall or shall not be applicable for a technical requirement which is classified "conditional"

Test Specification:

E/O Indicates whether the test specification forms part of the Essential Radio Test Suite (E) or whether it is one of the Other Test Suite (O)

NOTE: All tests whether "E" or "O" are relevant to the requirements. Rows designated "E" collectively make up the Essential Radio Test Suite; those designated "O" make up the Other Test Suite; for those designated "X" there is no test specified corresponding to the requirement. The completion of all tests classified "E" as specified with satisfactory outcomes is a necessary condition for a presumption of conformity. Compliance with requirements associated with tests classified "O" or "X" is a necessary condition for presumption of conformity, although conformance with the requirement may be claimed by an equivalent test or by manufacturer's assertion supported by appropriate entries in the technical construction file.

Clause Number Identification of clause(s) defining the test specification in the present document unless another document is referenced explicitly. Where no test is specified (that is, where the previous field is "X") this field remains blank.

Annex B (informative): Environmental profile specification

The following environmental conditions may be declared by the supplier:

- barometric pressure: minimum and maximum;
- temperature: minimum and maximum;
- relative humidity: minimum and maximum;
- power supply: lower and upper voltage limit.

When operating outside the boundary limits of the declared operational environmental profile the equipment should not make ineffective use of the radio frequency spectrum so as to cause harmful interference.

Annex C (informative): Testing of gain for part band repeaters

C.1 Rationale for this test

The normative provisions of the present document specify the out-of band gain relative to the edge of one of the GSM bands specified in clause 4.1. The purpose of this informative annex is to define a test method which may be used to measure the out-of-band gain for a repeater which is designed to operate only over part of one of these bands. This test may be used for acceptance testing or for regulatory purposes.

Agree the performance requirements prior to this test being performed, since TS 145 005 [i.6] does not specify the out-of-band gain requirements within a GSM band for a such a repeater. Normally, the requirements for the uplink and downlink directions will be similar, but with the frequencies offset by 45 MHz or 95 MHz.

C.2 Gain outside pass band

C.2.1 Test purpose

To determine the net gain of the repeater outside its specified pass band (or bands), when this is less than a GSM band defined in clause 4.1 of the present document. Met always the out-of-band gain requirements of the present document, whether or not this test is also performed.

This test is not a normative requirement of the present document.

C.2.2 Test case

Set the repeater to maximum gain. In case of a channel selective repeater, two of the channel selective set the modules to the lowermost and the uppermost ARFCN within the repeaters pass band.

Feed a continuous sinusoidal RF signal successively at each specified frequency into the relevant input port of the repeater. Set the power level of the RF input signal to at least 5 dB below the power level which would produce, when applied within the specified pass band, maximum rated output power, as declared by the manufacturer. This is to ensure that the equipment is operating in the linear output range.

Measure the average output power in each case and record the net gain.

Apply the measurements to all antenna ports of the repeater.

Test environment: normal
extreme temperature

C.2.3 Conformance requirement

The requirement is met, if the gain through the repeater at each frequency specified to be measured is less than the specified value.

Annex D (informative): The EN title in the official languages

The enlargement of the European Union (EU) resulted in a requirement from the EU for a larger number of languages for the translation of the titles of Harmonized Standards and mandated ENs that are to be listed in the Official Journal to support the implementation of this legislation.

For this reason the title translation concerning the present document can be consulted via the [e-approval](#) application.

Annex F (informative): Bibliography

- Directive 2004/108/EC of the European Parliament and of the Council of 15 December 2004 on the approximation of the laws of the Member States relating to electromagnetic compatibility and repealing Directive 89/336/EEC (text with EEA relevance (EMC Directive))
- Council Directive 73/23/EEC of 19 February 1973 on the harmonization of the laws of Member States relating to electrical equipment designed for use within certain voltage limits (L.V Directive)
- ETSI TR 121 905 (V8 8 0): "Digital cellular telecommunications system (Phase 2+); Universal Mobile Telecommunications System (UMTS); LTE; Vocabulary for 3GPP Specifications (3GPP TR 21 905 version 8 8 0 Release 8)"

History

| Document history | | | |
|-------------------------|---------------------|--|---|
| <u>V9 1 0</u> | <u>March 2010</u> | <u>One-step Approval Procedure</u> <u>(Withdrawn)</u> | <u>OAP 20100630: 2010-03-02 to 2010-06-30</u> |
| <u>V9 1 1</u> | <u>March 2010</u> | <u>Public Enquiry</u> | <u>PE 20100710: 2010-03-12 to 2010-07-12</u> |
| <u>V9 2 0</u> | <u>August 2010</u> | <u>Vote</u> | <u>V 20101019: 2010-08-20 to 2010-10-19</u> |
| <u>V9 2 1</u> | <u>October 2010</u> | <u>Publication</u> | |
| | | | |